



Astro Power Series

ATX-AS450W



20+4 PIN Exposed (500mm)x1 ; 12V P4 Exposed (500mm)x1
 PATA Exposed (400mm)+PATA(150mm)+SATA(150mm)+FDD(150mm)x1
 PATA Exposed (400mm)+SATA(150mm)+SATA(150mm)x1
 Total : (20+4Px1 , P4x1 , PATAx3 , SATAx3 , FDDx1)

AC Input	115-230VAC , 8A/4A , 50-60HZ				
DC Output Voltage	+3.3V	+5V	+12V	-12V	+5Vsb
Max Output Current	16A	16A	32A	0.3A	2.5A
Combined Power	100W	384W	3.6W	12.5W	
Total Power	450W				

ATX-AS500W




20+4 PIN Exposed (500mm)x1 ; 12V P4 Exposed (500mm)x1
 PATA Exposed (400mm)+PATA(150mm)+SATA(150mm)+FDD(150mm)x1
 PATA Exposed (400mm)+SATA(150mm)+SATA(150mm)x1
 Total : (20+4Px1 , P4x1 , PATAx3 , SATAx3 , FDDx1)

AC Input	115-230VAC , 8A/4A , 50-60HZ				
DC Output Voltage	+3.3V	+5V	+12V	-12V	+5Vsb
Max Output Current	16A	16A	36A	0.3A	2.5A
Combined Power	100W	432W	3.6W	12.5W	
Total Power	500W				



Astro Power Series

ATX-AR500W



20+4 PIN Sleevings(500mm)x1 ; 12V P4 Exposed (500mm)x1
 PATA Exposed (400mm)+PATA(150mm)+SATA(150mm)+FDD(150mm)x1
 PATA Exposed (400mm)+SATA(150mm)+SATA(150mm)+FDD(150mm)x1
 PCIe 6+2P Exposed (400mm)x1
 Total : (20+4Px1 , P4x1 , PATAx4 , SATAx3 , FDDx1 , PCIe6+2Px1)

AC Input	115-230VAC , 8A/4A , 50-60HZ				
DC Output Voltage	+3.3V	+5V	+12V	-12V	+5Vsb
Max Output Current	16A	16A	36A	0.3A	2.5A
Combined Power	100W	432W	3.6W	12.5W	
Total Power	500W				

ATX-AD500W



20+4 PIN Sleevings(500mm)x1 ; 12V P4 Exposed (500mm)x1
 PATA Exposed (400mm)+PATA(150mm)+SATA(150mm)+FDD(150mm)x1
 PATA Exposed (400mm)+SATA(150mm)+SATA(150mm)+FDD(150mm)x1
 PCIe 6+2P Exposed (400mm)x1
 Total : (20+4Px1 , P4x1 , PATAx4 , SATAx3 , FDDx1 , PCIe6+2Px1)

AC Input	115-230VAC , 8A/4A , 50-60HZ				
DC Output Voltage	+3.3V	+5V	+12V	-12V	+5Vsb
Max Output Current	16A	16A	36A	0.3A	2.5A
Combined Power	100W	432W	3.6W	12.5W	
Total Power	500W				